



SSP

Safety System Products

SB-H00-EB-Q1A0-Q2A0-Q3D0-Q4A0-W03

Simplifier Box 253

Your advantages

To the downloads ►



we simplify safety



Safety System Products

SB-H00-EB-Q1A0-Q2A0-Q3D0-Q4A0-W03

- SB-H00: Simplifier Box
- Lower housing: Color anthracite, no opening for connectors on the back
- Upper housing: Color gray, possible integration of three control points
- EB: Illuminated emergency stop button, 2 x NC
- Q1A0: Connector at the bottom left with cover
- Q2A0: Connector on top left with cover
- Q3D0: Bottom right male connector M12 8-pin
- Q4A0: Connector on top right with cover
- W03: already prewired

General data

Function type	Emergency stop
Type designation	SB-H00-EB-Q1A0-Q2A0-Q3D0-Q4A0-W03
Functional type	Operating unit
Product name	Simplifier Box 253

Button position 1

Type designation	E2
Item number	SP-x-87-000-22

Connection

- Position 3	Q3D0- Bottom right male connector M12 8-pin
--------------	---

Safety data

Approvals	CE
-----------	----

Environmental conditions

Max. storage temperature	□20 ... + 65 °C
Max. operating temperature	□20 ... + 65 °C

Electrical data

Button position 1

Type designation	EA
Utilisation category	DC13
	< 50 mOhm

SB-H00-EB-Q1A0-Q2A0-Q3D0-Q4A0-W03

mechanical lifespan	50.000 switching cycles
Number of pins	6

Wire size

Single - wire	0,20 ... 0,5 mm ²
Fine - wire	0,20 ... 0,5 mm ² mm ²
Fine - wire (wire end ferrule with plastic collar)	0,20 ... 0,5 mm ²
Fine - wire (wire end ferrule without plastic collar)	0,25 mm ²
Wire stripping	5 ... 6 mm

Mechanical data

Installation opening of buttons	22,5 mm
---------------------------------	---------

Housing type


Torque (mounting nut)	1,5-1,9 Nm
Width	42 mm
Length	253 mm

Dimensions


Height	44 mm
--------	-------

Equipment


Wireless Safety

Article code ZTK5	Button cap set for	SP-X-88-001-19	
	illuminated buttons		
Article code ZTK6	Button cap sets for unlit	SP-X-88-001-19	
	buttons		

SB-H00-EB-Q1A0-Q2A0-Q3D0-Q4A0-W03

	Inscription label set ZB1	SP-X-88-001-21	
	Inscription label set ZB2	SP-X-88-001-22	
	Inscription label set ZB3	SP-X-88-001-23	
Article code ZMT	Installation wrench	SP-X-88-001-25	
Article code ZUK	Liftingtool for button and light caps	SP-X-88-001-26	
Article code ZMB	Mounting plate big	SP-N-88-850-02	
Article code ZMS	Mountingplate small	SP-N-88-850-01	
Article code ZSD	Screw with seal	SP-X-88-001-89	

SB-H00-EB-Q1A0-Q2A0-Q3D0-Q4A0-W03

Artikelcode ZLK5	Signal light caps set for	SP-X-88-001-19	
	signal lights		
Fastening set for Safety Simplifier for back panel mounting	Simplifier ZHMS	SP-X-88-001-91	
Fastening set for Safety Simplifier	Simplifier ZHS	SP-X-88-001-91	

Downloads

- Product line
- Operating Instructions