



SSP

Safety System Products

SB-H0P-EA-IA-Q1A0-Q2A0-Q3D0-Q4A0-W04

Simplifier Box 253

Your advantages

To the downloads ►



we simplify safety



Safety System Products

SB-H0P-EA-IA-Q1A0-Q2A0-Q3D0-Q4A0-W04

- SB-H0P: Simplifier Box
- Lower housing: Color anthracite, no opening for connectors on the back
- Upper housing: Color gray, possible integration of three control points
- EA: Emergency stop button, 2 x NC
- Q1A0: Connector at the bottom left with cover
- Q2A0: Connector on top left with cover
- Q3D0: Bottom right male connector M12 8-pin
- Q4A0: Connector on top right with cover
- W04: already prewired

General data

Button position 1

Functional type	Operating unit
Function type	Not-Halt-Taster
Product name	Simplifier Box 253

Button position 2

Item number	SP-X-87-000-23
Type designation	E2
Type designation	SB-H0P-EA-IA-Q1A0-Q2A0-Q3D0-Q4A0-W04
Type designation	IA

Connection

- Position 3	Q3D0- Bottom right male connector M12 8-pin 250.000
	24 V DC

Safety data

Approvals	CE
-----------	----

Environmental conditions

Max. storage temperature	-20 ... + 65 °C
Max. operating temperature	-20 ... + 65 °C

Electrical data

Button position 1

we simplify safety

SB-H0P-EA-IA-Q1A0-Q2A0-Q3D0-Q4A0-W04

Type designation	EA
Connection type	Spring-loaded terminals
Bounce time NC	< 10 ms
Utilisation category	DC13
Rated voltage	24 V DC
	< 50 mOhm
mechanical lifespan	50.000 switching cycles
Number of pins	6
Wire size	
Single - wire	0,20 ... 0,5 mm ²
Fine - wire	0,20 ... 0,5 mm ² mm ²
Fine - wire (wire end ferrule with plastic collar)	0,20 ... 0,5 mm ²
Fine - wire (wire end ferrule without plastic collar)	0,25 mm ²
Wire stripping	5 ... 6 mm
	8

Mechanical data

Housing type

Installation opening of buttons	22,5 mm
Torque (mounting nut)	1,5-1,9 Nm
Width	42 mm
Length	253 mm

Dimensions

Height	44 mm
--------	-------

Equipment


Wireless Safety

Article code ZTK5


Button cap set for

SP-X-88-001-19

illuminated buttons



SB-H0P-EA-IA-Q1A0-Q2A0-Q3D0-Q4A0-W04

Article code ZTK6	Button cap sets for unlit	SP-X-88-001-19	
	buttons		
	Inscription label set ZB1	SP-X-88-001-21	
	Inscription label set ZB2	SP-X-88-001-22	
	Inscription label set ZB3	SP-X-88-001-23	
Article code ZMT	Installation wrench	SP-X-88-001-25	
Article code ZUK	Liftingtool for button and	SP-X-88-001-26	
	light caps		
Article code ZMB	Mounting plate big	SP-N-88-850-02	

SB-H0P-EA-IA-Q1A0-Q2A0-Q3D0-Q4A0-W04

Article code ZMS

Mountingplate small

SP-N-88-850-01



Article code ZSD

Screw with seal

SP-X-88-001-89



Artikelcode ZLK5

Signal light caps set for
signal lights

SP-X-88-001-19



Fastening set for Safety Simplifier for back panel
mounting

Simplifier ZHMS

SP-X-88-001-91



Fastening set for Safety Simplifier

Simplifier ZHS

SP-X-88-001-91



Downloads

- Product line
- Operating Instructions